


ANSI FL 1 Standard


MAIN WHITE - HIGH		1100 Lumens	61 M	3½ H
MAIN WHITE - LOW		500 Lumens	32 M	7 H
TOP TORCH		220 Lumens	21 M	10 H
R / A / G - STATIC		--	--	24 H
R / A / G - 2Hz FLASH		--	--	30 H

OPERATION

- This switch operates WHITE LEDs -
Switch sequence: TOP TORCH > MAIN WHITE LEDs HIGH > MAIN WHITE LEDs LOW > OFF.
- This switch operates RED LEDs -
Switch sequence: RED STATIC > RED 2Hz FLASH > OFF.
- This switch operates AMBER LEDs -
Switch sequence: AMBER STATIC > AMBER 2Hz FLASH > OFF.
- This switch operates GREEN LEDs -
Switch sequence: GREEN STATIC > GREEN 2Hz FLASH > OFF.

[If left in any mode for over 3 seconds, the next press will turn off]


FEATURES

- Super bright 1100 lumen white 10W 6500k SMD LEDs
- Red / Amber / Green SMD LEDs for signalling
- Coloured LEDs have static and 2Hz flashing functions
- 4 Independent switches for easy operation
- Additional 220 lumen white 6500k SMD LED top torch
- Super tough aluminium & polycarbonate construction
- Built-in aluminium heat sink on the back
- Integral rotating hanging hook with magnets
- Multi-positional fold-out kick stand/hook
- IP54 dust and water resistant
- Impact resistant to 1m
- Red-to-Green charging indicator LED
- 1m high quality DC-USB charging cable included

BATTERY - 3.7v 4400mAh Li-ion Rechargeable Battery

WEIGHT - 334g

DIMENSIONS - 205 x 60 x 42mm


CHARGING

1. Only use the DC-USB 5V cable supplied (do not use any other cables or chargers).
2. Lift the charging port cover on the back of the light.
3. Plug the DC end of the cable into the charge port.
4. Plug the USB end of the cable into a USB charging port.
(do not exceed 5V 2A output or damage may occur)
5. Charge Time: 4-5 hours
6. Red LED = indicates charging / Green LED = Fully charged

(PRODUCT CAN BE USED WHILE RECHARGING)

Warranty void if not used with the specified charger



